INVERTER PETROL GENERATOR

1 YEAR WARRANTY

PRODUCT SPECIFICATIONS SHEET

Manual Start | Unleaded Petrol

Inverter | Generator | 2 Stroke oil



The compact housing makes it great for everyday use.
The mute noise reduction gives an even more pleasant experience.
It just needs oil and petrol before use.

Ensure that generators are serviced after 30hours of operation
or every 6 months , which ever comes first .
In order to avoid warranty not being honored after 6 months.
please ensure to keep receipts of service at any
authorised service centers near you

Oil should be changed after the first 20-30 hours of operation
and every 100 hours of run time thereafter

CAUTION

Check oil and fill the tank before use! Use 2 STROKE generator oil!
Refer to owners manual for more information.

TOOI512	
Rated Output KVA / KW	2.0 / 2.0
Ratted Current (A)	8.7 A
Starting	Manual Start
12VDC O/P Rated Current	8.3 A
Engine Type	4 Stroke Force Air-Cooled
Fuel Tank	4 L
Displacement CC	105.7 CC
Run Time 0.75% Loading (Hrs)	4.5 Hours
Normal Running Speed (RPM)	3000
Size L x H x W (mm)	490mm x 440mm x 300mm
Dry Weight	TBA
Noise Level (7m)	61 db
Standard Items	Spark plug Wrench, Oil Refill Container, Open End Spanner, Screwdriver
ATS Code	None
Wheels	None

* T's & C's :
- Recommendation : Oil should be changed after the first 20-30 hours of operation and every 100 hours of runtime thereafter.
- Oil top up might be required.

HEAD OFFICE - JOHANNESBURG

P.O. Box 3812, Edenvale,
1610, South Africa
26 Nguni Drive
Longmeadow Estate West
Edenvale, Gauteng

www.acdc.co.za

BRANCH CONTACT DETAILS

Johannesburg	010 202 3300
Germiston	011 418 9600
Cape Town	021 510 0710
Pinetown	031 700 4215
Riverhorse	031 492 4800

NATIONAL CALL CENTRE: **010 202 3400**
TECHNICAL: **010 202 3500**

FOLLOW US ON