

Product SPECIFICATION SHEET



DHC3P-Meters

DHC® PANEL METER

DP3

3 1/2 DIGIT VOLTAGE , AMPERE METER

- DIN-size (48H x96Wmm) .
- 0.56Inch LED Display .
- Dual slope A/D conversion, high anti-interference.
- Measurement precision, performance reliable.

ORDERING CODE

<p>DP3- A - V</p> <p>V: Voltage A: Ampere A: AC D: DC</p> <p>3 1/2 Digit display Panel meter</p>	<p>DP3-A-V(V)</p> <table border="1"> <thead> <tr> <th></th> <th>5</th> <th>6</th> <th>7</th> <th>8</th> </tr> </thead> <tbody> <tr> <td>1</td> <td>600*</td> <td></td> <td></td> <td></td> </tr> <tr> <td>2</td> <td></td> <td>199.9</td> <td></td> <td></td> </tr> <tr> <td>3</td> <td></td> <td></td> <td>19.99</td> <td></td> </tr> <tr> <td>4</td> <td></td> <td></td> <td></td> <td>1.999</td> </tr> </tbody> </table> <p>600V</p>		5	6	7	8	1	600*				2		199.9			3			19.99		4				1.999
	5	6	7	8																						
1	600*																									
2		199.9																								
3			19.99																							
4				1.999																						
<p>AC DIGIT VOITMETER: Direct Input: AC 600V, 199.9V, 19.99V, 1.999V PT Input: It according to customer's offers</p> <p>AC DIGIT AMMETER: CT Input (:5A) : 10A, 15A, 20A, 50A, 100A, 150A, 200A, 500A, 1000A, 500A 2000A Direct Input:5A</p>	<p>DP3-D-A(A)</p> <table border="1"> <thead> <tr> <th></th> <th>1</th> <th>2</th> <th>3</th> <th>4</th> </tr> </thead> <tbody> <tr> <td>5</td> <td>500</td> <td>50.0</td> <td>5.00</td> <td>0.500</td> </tr> <tr> <td>6</td> <td>1000*</td> <td>100.0</td> <td>10.00</td> <td>1.000</td> </tr> <tr> <td>7</td> <td>1500</td> <td>150.0</td> <td>15.00</td> <td>1.500</td> </tr> <tr> <td>8</td> <td>2000</td> <td>200.0</td> <td>20.00</td> <td>2.000</td> </tr> </tbody> </table>		1	2	3	4	5	500	50.0	5.00	0.500	6	1000*	100.0	10.00	1.000	7	1500	150.0	15.00	1.500	8	2000	200.0	20.00	2.000
	1	2	3	4																						
5	500	50.0	5.00	0.500																						
6	1000*	100.0	10.00	1.000																						
7	1500	150.0	15.00	1.500																						
8	2000	200.0	20.00	2.000																						
<p>DC DIGIT VOITMETER: Direct Input: DC 600V, 199.9V, 19.99V, 1.999V</p> <p>DC DIGIT AMMETER: CT Input (:75mV/50mV) : 10A, 15A, 20A, 50A, 100A, 150A, 200A, 500A, 1000A, 500A 2000A</p>	<p>DP3-A-A (A)</p> <table border="1"> <thead> <tr> <th></th> <th>5</th> <th>6</th> <th>7</th> <th>8</th> </tr> </thead> <tbody> <tr> <td>1</td> <td>500</td> <td>1000</td> <td>1500</td> <td>1999</td> </tr> <tr> <td>2</td> <td>50.0</td> <td>100.0</td> <td>150.0</td> <td>199.9</td> </tr> <tr> <td>3</td> <td>5.00*</td> <td>10.00</td> <td>15.00</td> <td>19.99</td> </tr> </tbody> </table> <p>5.00A</p>		5	6	7	8	1	500	1000	1500	1999	2	50.0	100.0	150.0	199.9	3	5.00*	10.00	15.00	19.99					
	5	6	7	8																						
1	500	1000	1500	1999																						
2	50.0	100.0	150.0	199.9																						
3	5.00*	10.00	15.00	19.99																						

BRANCH CONTACT DETAILS

Johannesburg 010 202 3300
Germiston 011 418 9600
Cape Town 021 510 0710
Pinetown 031 700 4215
Riverhorse 031 492 4800

NATIONAL CALL CENTRE

Sales 010 202 3400
Technical 010 202 3500

www.acdc.co.za